

*Features*

- Premium Audio Performance
- Wide Frequency Response
- Very Low Insertion Loss
- Up to 100 watts
- A Must for KSI Loudspeakers

KSI audio transformers are designed for use in both 25 and 70.7 volt distributed sound systems. Heavy steel cores assure very low distortion and wide frequency response. This is essential, as our transformers will not degrade the high performance found in all KSI loudspeakers. Compared to small cheap transformers from other manufactures, KSI transformers are of consistent and high quality, providing you with top audio performance for all of your distributed sound systems. Our ELT series provides exceptional performance by offering extended low frequency response.

The response over the entire range only varies by only 1 db!! KSI offers a full selection of sizes for any installation.



**TRANSFORMER SPECIFICATIONS**

<b>25 Volt line</b>				
T25-8	T25-15	T25-30	T25-60	T25-100
ELT25-8	ELT25-15	ELT25-30	ELT25-60	ELT25-100
<b>70 Volt line</b>				
T70-8	T70-15	T70-30	T70-60	T70-100
ELT70-8	ELT70-15	ELT70-30	ELT70-60	ELT70-100
<b>Primary Taps Watts</b>				
2,4,8	5,10,15	10,20,30	20,40,60	25,50,100
<b>Frequency response</b>				
T series/ 50-15000 Hz +/- 3db				
ELT series/ 30-15000 Hz +/- 1db				
<b>Insertion loss</b>				
All transformers .5db				
<b>Secondary impedance</b>				
All transformers 4 & 8 ohms				